



Motor Rating		K.W	0.06	0.09	0.12	0.18	0.25	0.37	0.55	0.75	1.5	2.2	3	4	5.5	7.5	8	9	11	15	18.5	22	30	37	45	55	75	90	110	132	160	200	220
		Hp	0.08	0.12	0.16	0.24	0.34	0.5	0.75	1	2	3	4	5.5	7.5	10	11	12	15	20	25	30	40	50	60	75	100	125	148.7	180	220	270	###
Voltage 220/230V 3- Phase	Full load current	A	0.50	0.70	0.80	1.20	1.50	2.1	2.8	3.6	6.8	9.6	11.5	14.5	22	28	30	32	42	54	68	80	104	130	150	192	245	312	400	425	600	630	780
	Cable Size	mm2	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5	2.5	4	6	10	10	10	16	25	25	35	50	50	70	95	150	185	185	185			
Voltage 380/400V 3- Phase	Full load current	A	0.3	0.4	0.4	0.65	0.8	0.98	1.5	2	3.5	5	6.5	8.4	11	14.8	16.5	18	21	29	35	42	57	69	81	100	135	165	200	240	285	352	388
	Cable Size	mm2	1.5	1.5	1.5	1.5	1.5	1.5	1.5	4	6	6	4	6	6	10	10	10	10	50	50	50	50	50	120	120	120	150	185	240	240	2x150	2x151
Voltage 480/500V 3- Phase	Full load current	A	0.3	0.4	0.4	0.6	0.8	1	1.21	1.5	2.6	3.8	5	6.5	9	12	13.9	15.5	18.4	23	28.5	33	45	55	65	94.5	105	129	156	187	220	281	310
	Cable Size	mm2	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5	2.5	4	4	4	6	10	10	16	25	25	35	50	50	70	95	150	150	185	185